

PowerWalker VI 1500 LCD

Line-Interactive UPS

1500VA Line-Interactive UPS

2x Schuko + 2x IEC outlets, RJ11/RJ45 Surge Protection

USB Connection for monitoring

LCD display for status view

Built-in boost and buck AVR function




Item-No. 10120019



Product Features

PowerWalker VI 1500 LCD is a Line- Interactive UPS which provides high performance and reliable and cost-effective backup power protection. The UPS can be automatically started up without AC power supplied. In addition, this UPS provides RJ11/RJ45 surge protection, and green power function for energy saving. Equipped with a voltage stabilizer, this UPS will continue providing clean and stable power to connected equipment and is perfect for any home or SMB (small medium business) application.

- Super smart charger to shorten charging time
- Built-in boost and buck AVR
- Simulated sine wave
- Auto restart while AC is recovering
- Off-mode charging
- Cold start function
- USB communication port
- RJ11/RJ45 surge protection
- Monitoring software included
- LCD display for status view



Technical Details

Product Features

Capacity	1500VA / 900W
----------	---------------

Input

Voltage	220/230/240VAC
---------	----------------

Voltage Range	160-290VAC
---------------	------------

Output

Voltage	220/230/240VAC
---------	----------------

Voltage Regulation	± 10 % (Battery Mode)
--------------------	-----------------------

Frequency	50 or 60Hz
-----------	------------

Freq. Regulation	±1 Hz (Battery Mode)
------------------	----------------------

Waveform	Modified Sine wave
----------	--------------------

Transfer Time

Typical	2-6ms
---------	-------

Battery

Type	12V / 9Ah
------	-----------

Quantity	2 x
----------	-----

Recharge Time	4h to 90%
---------------	-----------

Full Protection

Discharge	Yes
-----------	-----

Overcharge	Yes
------------	-----

Overload	Yes
----------	-----

LCD Display

LCD Indicators	AC mode, Battery mode, Load level, Battery capacity, Input voltage, Output voltage, Overload alarm, Fault alarm and Low battery alarm.
----------------	--

Audio Indicators

Battery Mode	Beep every 10sec
--------------	------------------

Low Battery	Beep every second
-------------	-------------------

Fault	Beep every 0.5sec
-------	-------------------

Battery Weak	Beep every 2sec
--------------	-----------------

Battery faulty	Continuously sounding
----------------	-----------------------

Connections

Communication	USB
---------------	-----

Outlets	2x Schuko and 2x IEC
---------	----------------------

Surge Protection	RJ11/RJ45 (in/out)
------------------	--------------------

Software & System Requirements

Software	ViewPower
----------	-----------

Operating System	For details visit: www.powerwalker.com/viewpower.html
------------------	--

Other	1x USB port
-------	-------------

Product Details

Dimensions	397 x 146 x 205 mm
------------	--------------------

Colour	Black
--------	-------

Weight UPS case	10.7kg
-----------------	--------

Fan Control	Auto OFF: in LINE mode ON: in battery- and AVR mode
-------------	---

Noise Level	< 40dB
-------------	--------

Model Code	VI 1500 LCD
------------	-------------

Environment

Temperature	0°C – 40°C
-------------	------------

Humidity	0 - 90% (non-condensing)
----------	--------------------------

Package Content

Package Content	PowerWalker VI 1500 LCD, Input Power cable, IEC cable, Software CD, USB cable, manual
-----------------	---

Logistic Data

Giftbox Language	EN/DE/FR/ES/IT/PT/SV/FI/NO/TR RU/UA/BY/PL/CZ/HR/HU/BG/KK/SR
------------------	--

Manual Language	EN/DE/FR/ES/IT/PT/SV/FI/NO/TR RU/UA/BY/PL/CZ/HR/HU/BG/KK/SR
-----------------	--

Dimension/Giftbox	495 x 230 x 290 mm
-------------------	--------------------

Weight/Giftbox	11.8kg
----------------	--------

Pieces/Carton	1
---------------	---

Pieces/Palette	42
----------------	----

Item Number	10120019
-------------	----------

EAN	4260074972788
-----	---------------

Warranty	24 Month (except battery)
----------	---------------------------

Version: EN 13/01/2014

We reserve the right for technical changes and mistakes

Use UPS configurator on www.powerwalker.com for detailed backup time information.

PowerWalker is a brand of:

BlueWalker GmbH

Martin-Buber-Strasse 12 • D-41470 Neuss • Germany

Phone: +49 (0) 2137 / 92 98 73 • Fax: +49 (0) 2137 / 78 73 925

info@bluewalker.eu • www.bluewalker.eu • www.powerwalker.com

Available accessories



Yuasa 12V/7Ah battery
 Datasheet: [Link](#)
 CSB or Panasonic brand can also be used



Yuasa 12V/9Ah battery
 Datasheet: [Link](#)
 CSB or Panasonic brand can also be used



USB cable
 Item Nr.: 91010011



ATS (Automatic Transfer Switch)
 Datasheet: [Link](#)
 Item No.: 10120543



MBS (Maintenance Bypass Switch)
 Datasheet: [Link](#)
 Item No.: 10120500



Schuko Input -> IEC C13
 Item Nr.: 91010017



UK Input -> IEC C13
 Item Nr.: 91010029

Swiss Input -> IEC C13



IEC C13 -> IEC C14
 Item Nr.: 91010013



Schuko Input -> IEC C19
 Item Nr.: 91010018

UK Input -> IEC C19
 Item Nr.: 91010030

Swiss Input -> IEC C19



IEC C19 -> IEC C20
 Item Nr.: 91010028



IEC C13 -> IEC C20
 Item Nr.: 91010041



IEC C14 -> IEC C19
 Item Nr.: 91010040



IEC C14 -> Schuko
 Converter
 Item Nr.: 91015003



Schuko -> UK adaptor
 Item Nr.: 91010031