



Aspire 3

- Intel[®] Pentium[®] Processor¹
- Precision Touchpad
- BlueLightShield™
- Full High-Definition¹
- ${\bf 1.}\ \ {\bf Specifications}\ {\bf vary}\ {\bf depending}\ {\bf on}\ {\bf model}\ {\bf and/or}\ {\bf region}.$











180-Degree lay flat









Gigabit LAN

BluelightShield™



Product views		5. HDMI [®] port	9.		13. DC-in jack for power adapter
		USB 3.0 port		0. Touchpad	
		 SD™ card slot 		1. Headset/speaker jack	
01.2	4. Ethernet (RJ-45) port Windows 10 Home 64-bit	8. Power button	1;	2. Two USB 2.0 ports	
Operating system ^{1, 2}	Intel® Pentium® quad-core processor N371	10 Intel® Celeron® du	ial coro processor	N2060	
CPU and chipset ¹	Intel® Celeron® quad-core processor N316	0 Intel[®] Atom[®] quad			
Memory ^{1, 3, 4, 5}	Single-channel DDR3L SDRAM support with • Upgradable to 8 GB of DDR3L system me	mory using a single soDIMI			
Display		15.6" HD 1366 x 768 resolu		6.6" HD 1366 x 768 resolution,	15.6" HD 1366 x 768 resolution,
		high-brightness Acer Com		gh-brightness Acer CineCrystal™	high-brightness Acer CineCrystal™
		LED-backlit TFT LCD		D-backlit TFT LCD	LED-backlit TFT LCD
		 16:9 aspect ratio Ultra-slim design 		16:9 aspect ratio Ultra-slim design	16:9 aspect ratioSuper-slim design
		 Mercury free, environme 		Mercury free, environment friendly	 Mercury free, environment friend
Graphics ⁷	Intel® HD Graphics	• Mercury free, environme	incrinently •	recury free, environment menaty	• Mercury free, environment menu
Audio	Two built-in stereo speakers				
Charage 1.8	Built-in digital microphone Hard disk drive:				
Storage ^{1, 8}	• 1 TB / 500 GB 2.5-inch 5400 RPM				
Webcam ¹	Acer webcam with:				
	 640 x 480 resolution 				
Wireless and	WLAN:				
networking ¹	 802.11ac/a/b/g/n wireless LAN 				
.	Operates at 2.4 GHz and 5 GHz				
	Intel® Dual Band Wireless-AC, 802.11ac/a/b/g/n 1X1 wireless LAN				
	LAN:				
	Gigabit Ethernet, Wake-on-LAN ready				
	WPAN: • Bluetooth® 4.1				
Security ¹	Firmware Trusted Platform Module (TPM) so	olution			
Security	BIOS user, supervisor, HDD passwords				
	Kensington lock slot		101		
Dimensions and weight ⁶	Dimensions: • 381.6 (W) x 262.8 (D) x 21.6 (H) mm (15.0	2 x 10.35 x 0.85 inches)		eight: 2.1 kg (4.63 lbs.) with 2-cell battery	pack
Power adapter and	Power adapter:			3,,	F
the state of the s	• 3-pin 45 W AC adapter:				
battery ⁹	Battery:				
	37 Wh 4810 mAh 7.7 V 2-cell Li-ion battery				
	 Battery life up to 7 hours 	•			
Input and control	Keyboard:				
	103-/104-/107-key FineTip keyboard with independent standard numeric keypad, international language support, power button				
	Media Keys:				
	Media control keys (printed on keyboard): volume up, volume down				
	Touchpad: Multi-gesture touchpad, supporting two-finger scroll; pinch; gestures to open Cortana, Action Center, multitasking; application commands				
	 Microsoft Precision Touchpad certification Moisture resistant 	on			
Windows Desktop	Acer Care Center	Quick Acco	000	• Cuborli	nk® PhotoDirector 8
apps ¹⁰	Acer Care Center Acer Collection	MS Remot			nk [®] PowerDirector 14
Options and	3-pin 45 W AC adapter	- 1-15 Remot	Съскор	- cyberni	TOWEIDHEELDI 14
accessories	5 piii 45 W Ac adapter				
Warranty	One-year International Travelers Warranty	(ITW)			
Specifications vary de		(11 **)	8. 1 GB is 1 I	pillion bytes 1 TR is 1000 GR Actual format	tted capacity is less and may vary depending on
	pending on model. Jired to enjoy the advantages of 64-bit processing.				cted capacity is less and may vary depending on covery Management uses a portion of the stated
Shared system memor	y may be allocated to support graphics, depending on sy	stem memory size and	hard disk	capacity as dedicated backup space.	
	ystem memory available to the operating system will be				ductivity mode testing with wireless on. Details
	olution and resources required by the operating environr ry, depending on the CPU, chipset or memory fitted.	ment.		ark 2014 testing are available at www.bapco	
A 64-bit operating sys	B or higher memory.	purposes only. Actual battery life varies by model, configuration, application, power management mory. settings, operating conditions, and features used. A battery's maximum capacity decreases with tim			
Weight may vary depe	nding on product configuration, vendor components, ma	anufacturing variability,	and use.		
and selected options.	es depend on display capability and color/depth settings		Bundled s	oftware may vary depending on hardware o	configuration, OS and regional availability.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

© 2018. All rights reserved.

Microsoft and Windows are registered trademarks of Microsoft Corporation.

Intel, Intel Core, Core Inside, Pentium, and Pentium Inside are trademarks of Intel Corporation in the U.S. and other countries.

Resolution/refreshrates depend on display capability and color/depth settings.

About Acer