

## Aspire E 11

ES1-111 / ES1-111M E3-112 / E3-



## **SPECIFICATIONS**





Product views	1 Webcam 2 11.6" HD 1366 x 768 resolution LCD 3 FineTip keyboard 4 Precision touchpad 5 Power button	6 Headset/speaker jack 7 SD Card reader 8 DC-in jack for AC adapter 9 Ethernet (RJ-45) LAN port	<ul> <li>10 USB 2.0 port</li> <li>11 USB 3.0 port</li> <li>12 HDMI<sup>®</sup> port with HDCP support</li> <li>13 Kensington lock slot</li> </ul>
Operating system <sup>1, 2</sup>	Windows 8.1 64-bit		
CPU and chipset <sup>1</sup>	Intel® Pentium® N3530 processor	Intel® Celeron® N2830 processor	Intel <sup>®</sup> Celeron <sup>®</sup> N2930 processor
Memory <sup>1, 3, 4, 5</sup>	DDR3L SDRAM support with up to 8 GB of DDR3L system memory		
Display	11.6" HD 1366 x 768 resolution, high-brightness Acer ComfyViewTM LED- backlit TFT LCD 16:9 aspect ratio, ultra-slim design Mercury free, environment friendly		
Graphics <sup>1, 6</sup>	Intel® HD Graphics with 64 MB of dedicated system memory HDMI® (High-Definition Multimedia Interface) with HDCP 1.3 (High- bandwidth Digital Content Protection) support		
Audio	High-definition audio support Two buil	t-in stereo speakers MS-Sound compatible	Built-in microphone
Storage <sup>7</sup>	Hard disk drive: 320 / 500 GB / 1 TB 2.5-inch 54 RPM	Card reader: SD Card	
Webcam <sup>1</sup>	Video conferencing: Acer Crystal Eye HD webcam,1280 x 720 resolution, 720p HD audio/video recording		
Wireless and networking <sup>1, 8, 9</sup>	<b>WLAN:</b> Acer InviLink <sup>™</sup> Nplify <sup>™</sup> 802.11b/g/n wireless LAN	WPAN: Bluetooth <sup>®</sup> 4.0	LAN: Gigabit Ethernet, Wake-on-LAN ready
Privacy control <sup>1</sup>	Kensington lock slot		
Dimensions and weight <sup>10</sup>	Dimensions: 291 (W) x 211 (D) x 21.2/21.2 (H) mm (11.46 x 8.31 x 0.83/0.83 inches) Weight: 1.29 kg (2.84 lbs.) with 3-cell battery pack		
Power adapter and battery <sup>11</sup>	Power adapter: 3-pin 40 W AC adapter Battery: 36 Wh 3220 mAh 11.4 V 3-cell Li-ion battery pack , battery life up to 5 hours		
Input and control	Keyboard: 83-/84-/87-key full-size Acer FineTip keyboard with international language support  Touchpad: Multi-gesture touchpad, supporting two-finger scroll and pinch. Swipes access charms, application commands		
Windows Store Apps <sup>12</sup>	Acer branded  • Acer Explorer		
Windows Desktop Apps 12	Acer branded  • Acer Accessory Store  • Acer Docs  • Acer Identity Card  • Acer Live Updater  • Acer Media  • Acer Photo	Acer Portal     Acer Power Management     Acer Recovery Management     Acer Registration     Acer Remote Files     Acer Video Player	Productivity     Office 2013 Security     McAfee® Anti-Theft shortcut
Options and accessories	Acer HDMI <sup>®</sup> -to-VGA converter		
Warranty	One-year International Travelers Warranty (ITW)		

- Specifications vary depending on model.

  64-bit software is required to enjoy the advantages of 64-bit processing.

  Shared system memory may be allocated to support graphics, depending on system memory size and other factors. Actual system memory available to the operating system will be reduced by any memory used by the graphics solution and resources required by the operating environment.

  Memory speed may vary, depending on the CPU, chipset or memory fitted.

  A 64-bit operating system is required to enjoy the ultimate performance of 4 GB or higher memory.

  Resolution/refresh rates depend on display capability and color/depth settings.

  1 GB is 1 billion bytes, 1 TB is 1000 GB. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Acer Recovery Management uses a portion of the stated hard disk capacity as dedicated backup space.

- Actual throughput may vary depending on network conditions and environmental factors such as network traffic or overhead, building construction and access point settings. Subject to availability. Weight may vary depending on product configuration, vendor components, manufacturing variability, and
- 9. 10.
- Weight may vary depending on phosos of the selected options.
   The listed battery life is based on MobileMark 2012<sup>®</sup> productivity mode testing with wireless on. Details of MobileMark 2012<sup>®</sup> testing are available at www.bapco.com. Battery life rating is for comparison purposes only. Actual battery life varies by model, configuration, applications, power management settings, operating conditions, and utilized features. A battery's maximum capacity decreases with time and use.
   Bundled software may vary depending on hardware configuration, OS and regional availability.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary

depending on region.
© 2014. All rights reserved.
Microsoft and Windows are registered trademarks of Microsoft Corporation. Intel, Pentium, Pentium Inside and Celeron are trademarks of Intel Corporation in the U.S. and other countries.

